

BR-HD50 Recording/playback format

	Recording (Analog output)	Tape	Component out/ HDMI out	Video out	PAL	NTSC
DV	480i 60	←	A	480i 60		0
	576i 50	←	B	576i 50	0	

	Playback	IEEE 1394	Component out/ HDMI out	Video out	PAL	NTSC
HDV	720p 60	←	A (Upgrade resulted)	480i 60 (Upgrade resulted)	0	0
	720p 30	←	A	480i 60	0	0
	720p 50	←	B (Upgrade resulted)	576i 50 (Upgrade resulted)	0	0
	720p 25	←	B	576i 50	0	0
	720p 23.98	←	A	480i 60	0	0
	480p 60	←	A	480i 60	0	0
DV	576p 50	←	B	576i 50	0	0
	480i 60	←	A	480i 60		0
	576i 50	←	B	576i 50	0	
	480i 60 (23.98)	←	A	480i 60		0
	576i 50 (25)	←	B	576i 50	0	

	Recording (IEEE1394 output)	Tape	Component out/ HDMI out	Video out	PAL	NTSC
HDV	720p 30	←	A	480i 60	0	0
	720p 25	←	B	576i 50	0	0
	720p 23.98	←	A	480i 60	0	0
	480p 60	←	A	480i 60	0	0
	576p 50	←	B	576i 50	0	0
DV	480i 60	←	A	480i 60		0
	576i 50	←	B	576i 50	0	
	480i 60 (23.98)	←	A	480i 60		0
	576i 50 (25)	←	B	576i 50	0	

A: 720p 60, 480p 60, 1080i 60, 480i 60 B: 720p 50, 576p 50, 1080i 50, 576i 50 Note: 30 = 29.97 Hz 60 = 59.94 Hz

*Tapes recorded in HDV 1080i format cannot be played back by BR-HD50.